

Wireless Bi-directional audio to and from your mixer

+

+



GSM-LINK



Features

High quality Hybrid circuit
Wireless audio up to 24 bit/96kHz
Bi directional audio
Direct acces CONN/PLAY/PAUSE button



Hardware

Unbalanced Audio in/Out
GPI and GPO connectors
Stereo Line in/output
Desktop and drothrough mounting

The Wireless Connection

Wireless Connectivity with the help of your GSM phone

The D&R GSM-LINKJ is your gateway to wireless communication, allowing you to take calls and send stereo audio to your mixing console in an easy and effortless way.

With this bi-directional GSM-LINK, you can integrate a robust wireless interface into your studio, enabling clear and direct calls from the field with the help of your Phone.

GSM-LINK features

The GSM-LINK uses our high quality Telephone Hybrid circuit to enable you to accept and make calls on your Phone during your broadcast.

It also supports high quality wireless audio, so playing stereo music from Spotify on your mixer has never been easier.

To make live easy hit the “all in one switch” on the GSM-LINK to play/pause your music.

Included in the package is an external 12-volt power supply adapter.

Transform your studio’s communication capabilities with the D&R GSM Hybrid, the ideal replacement for outdated landline Hybrids.

SPECIFICATIONS

Line input:	Unbalanced, 10kOhm + 4 dBu max,
Frequency response:	20Hz up to 20kHz
Output:	Unbalanced, 50 Ohm + 4 dBu max
GPO:	Opto Fet 60V/550mA Pmax=500mW
GPI:	Pulldown to GND.
Tip:	uses opto coupler.
Frequency band:	2.4 GHz band
Antenna:	Built in

DIMENSIONS/WEIGHT

Left-Right:	90mm
Front to back:	110mm
Height:	32-38mm
Front thickness:	2mm
Weight:	1kg
Power:	90-240volt 50/60Hz
Voltage:	12Vdc
Supply Current:	0.5 Amp

